

Bliss Electronic Co. Ltd.

2F, No. 2, Lane 348, Sec. 2, Chung Shan Rd. Chung Ho City, Taipei Hsien, 235, Taiwan

Web Site: www.bliss.com.tw Tel: 886-02-22466201 Fax: 886-02-22482374

Model	BRM-08M	Recordable Card	Category	Card
Feature	<ul style="list-style-type: none"> - New thin housing (4.5mm thin). - Great as module of collector's card, - Great for Music, TV, and movie promotions. - Idea to fit inside gift packaging. - Replaceable battery. 			
Operation	<ul style="list-style-type: none"> - Press and hold both recording button to record. - Speak to the microphone with normal volume at 5~10cm distance. - Press "PLAY" to play the message 			
IC Function	15 seconds recordable IC			
Operation Current	$\leq 75\text{mA}$	Play time	100 time (record once + 15 seconds playback)	
Standby Current	$\leq 1\mu\text{A}$	Shelf Life		
Input / Switch	Thin Film Mylar Switches (Play x1, Record x2)			
LED / EL Brightness	N/A	Color & Quantity		
Sound Output	$\geq 80\text{ dB @ } 10\text{cm Distance}$ (Surrounding at $\leq 60\text{dB}$)	Speaker Size / Type	28Φ Mylar Speaker	
Operation Voltage	3V	Battery Type	CR2025 x1	
Size (WxHxD)	63(W)x76(H)x4.5(D) mm	Material	ABS	
Weight	18g (Battery Included)	Packing		
Spec Release Date	2005-11-03	Approval	Barry Hsieh	Engineer Andy Cheng